














## Absolute Maximum Ratings – 1SP0351V2A0C-5SNA3000K452300

Parameters	Symbol	Conditions $T_A = -40\text{ °C to }85\text{ °C}$	Min	Max	Unit
<b>Absolute Maximum Ratings<sup>1</sup></b>					
Primary-side supply voltage	$V_{V15}$	V15 to GND	0	16	V
Primary-side supply current	$I_{V15}$	Steady-state condition		360	mA
Switching Frequency	$f_{SW}$	Continuous operation		2	kHz
Gate output power	$P_G$	$T_A = 85\text{ °C}$		1.8	W
Gate output current	$I_G$			50	A
Test voltage primary-side to secondary-side	$V_{iso,ps}$	50 Hz, 60 s		10200	$V_{RMS}$
Operating voltage primary-side to secondary-side	$V_{op}$	Transient only		4500	$V_{pk}$
		Permanently applied		3400	$V_{DC}$
DC-link voltage	$V_{DLK}$	Switching operation		3400	V
		Off-state, limited to 60 s		4000	V
Storage temperature <sup>2</sup>	$T_{stg}$		-40	50	°C
Operating ambient temperature	$T_A$		-40	85	°C
Surface temperature <sup>3</sup>	$T_{sf}$			125	°C
Relative humidity	$H_r$	No condensation		93	%
Altitude of operation <sup>4</sup>	$A_{op}$			2000	m

Notes:

-  Stresses beyond those listed under absolute maximum ratings may cause permanent damage to the device.
- The storage temperature inside the original package or in case the coating material of coated products may touch external parts must be limited to the given value. Otherwise, it is limited to 85°C.
- The component surface temperature, which may strongly vary depending on the actual operating conditions, must be limited to the given value for coated gate driver versions to ensure long-term reliability of the coating material.
- Operation above this level requires a voltage derating to ensure proper isolation coordination.

## Recommended Operating Conditions – 1SP0351V2A0C-5SNA3000K452300

Parameter	Symbol	Conditions $T_A = -40\text{ °C to }85\text{ °C}$	Min	Typ	Max	Unit
<b>Power Supply</b>						
Primary-Side Supply Voltage	$V_{V15}$	V15 to GND	14.5	15	15.5	V

**Characteristics – 1SP0351V2A0C-5SNA3000K452300**

Parameter	Symbol	Conditions $T_A = 25\text{ °C}$	Min	Typ	Max	Unit	
<b>Power Supply</b>							
<b>Supply current</b>	$I_{V15}$	$V_{V15} = 15\text{ V}$ , without load		150		mA	
		$V_{V15} = 15\text{ V}$ , $P_G = P_{G,max}$		280		mA	
<b>Power supply monitoring threshold (secondary-side)</b>	$UVLO_{V150}$	Referenced to terminal E	Clear fault (resume operation)	11.6	12.6	13.6	V
			Set fault (suspend operation)	11.0	12.0	13.0	V
			Hysteresis	0.35			V
	$UVLO_{COM}$		Clear fault (resume operation)		-5.15		V
			Set fault (suspend operation)		-4.85		V
			Hysteresis		0.3		V
<b>Output voltage (secondary-side)</b>	$V_{V150}$	Referenced to $V_{COM}$	$V_{V15} = 15\text{ V}$ , without load		24.4		V
			$V_{V15} = 15\text{ V}$ , $P_G = P_{G,max}$		24.1		V
<b>Coupling capacitance</b>	$C_{io}$	Primary-side to secondary-side		8		pF	
<b>Timing Characteristics</b>							
<b>Turn-on delay<sup>5</sup></b>	$t_{P(LH)}$	OIN to 50% of $V_{GE(on)}$ , no load attached (optical cable length 1 m)		100		ns	
<b>Turn-off delay<sup>5</sup></b>	$t_{P(HL)}$	OIN to 50% of $V_{GE(off)}$ , no load attached (optical cable length 1 m)		125		ns	
<b>Transmission delay of fault state<sup>6</sup></b>	$t_{OOUT}$	Optical cable length 1 m		100		ns	

Notes:

5. Measured from the transition of the turn-on or turn-off command at the optical transmitter of the external controller to the direct output of the gate drive unit (excluding the delay of the gate resistors).
6. Measured from the driver secondary-side (ASIC output) to the optical receiver on the external controller.



Parameter	Symbol	Conditions $T_A = 25\text{ }^\circ\text{C}$	Min	Typ	Max	Unit
<b>Timing Characteristics (cont.)</b>						
<b>Delay to clear fault state<sup>8</sup></b>	$t_{blk}$	Measured on the external controller side (optical cable length 1 m)		8		$\mu\text{s}$
<b>Acknowledge delay time<sup>9</sup></b>	$t_{d(ack)}$	Optical cable length 1 m		190		ns
<b>Acknowledge pulse width</b>	$t_{ack}$	Measured on the external controller side (optical cable length 1 m)	400	600	1050	ns
<b>Gate Output</b>						
<b>Gate turn-on voltage</b>	$V_{GE(on)}$	$V_{V15} = 15\text{ V}$ , without load, referenced to terminal E		15		V
		$V_{V15} = 15\text{ V}$ , $P_G = P_{G,max}$ referenced to terminal E		15		V
<b>Gate turn-off voltage</b>	$V_{GE(off)}$	$V_{V15} = 15\text{ V}$ , without load, referenced to terminal E		-9.4		V
		$V_{V15} = 15\text{ V}$ , $P_G = P_{G,max}$ referenced to terminal E		-9.1		V
<b>Short-Circuit Protection</b>						
<b>Static VCE-monitoring threshold</b>	$V_{CE(stat)}$			680		V
<b>Response time</b>	$t_{res}$	DC-link voltage = 3400 V		8		$\mu\text{s}$
		DC-link voltage = 2800 V		8		$\mu\text{s}$
		DC-link voltage = 1500 V		8		$\mu\text{s}$
<b>Delay to power semiconductor turn-off after short-circuit detection</b>	$t_{pd,SC}$			0.2		$\mu\text{s}$

Notes:

- The fault status is stretched by the given value after the fault condition has been turned-off.
- Measured from the transition of the turn-on or turn-off command at the optical transmitter of the external controller to the transition of the acknowledge signal at the optical receiver of the external controller.

Parameter	Symbol	Conditions $T_A = 25\text{ °C}$	Min	Typ	Max	Unit
<b>Electrical Isolation</b>						
<b>Test voltage</b> <sup>10</sup>	$V_{iso,ps}$	Primary-side to secondary-side	10.2			kV <sub>RMS</sub>
<b>Partial discharge extinction voltage</b> <sup>11</sup>	$P_{D,ps}$	Primary-side to secondary-side	5400			V <sub>pk</sub>
<b>Creepage distance</b>	$CPG_{P-S,PCB}$	On the PCB (Material group IIIa), Primary-side to secondary-side	45			mm
	$CPG_{P-S,Trf}$	On the transformer (Material group I), Primary-side to secondary-side	36			mm
<b>Clearance distance</b>	$CLR_{P-S}$	Primary-side to secondary-side	25			mm
<b>Mounting</b>						
<b>Terminal connection torque</b>	$M_{M4}$	Screw M4	1.8		2.1	Nm
<b>Bending</b> <sup>12</sup>	$l_{bend}$	According to IPC			0.75	%
<b>Gate Output</b>						
<b>Turn-on gate resistor</b>	$R_{G(on)}$			1.5		$\Omega$
<b>Turn-off gate resistor</b>	$R_{G(off)}$			7		$\Omega$
<b>Auxiliary gate capacitor</b>	$C_{GE}$			330		nF

Notes:

10. The transformer of every production sample has undergone 100% testing at the given value for 1s.
11. Partial discharge measurement is performed on each transformer. The measurements are performed in accordance with IEC 60270 and IEC 60664-1 for basic insulation requirements.
12. Refer to section Mounting Instruction for absolute values of allowed bending distances.

## Mounting Instruction

The gate driver has to be mounted on top of a suitable surface using the provided non-plated fixation holes S1 to S8 as shown in Figure 7. To avoid corona effects non-conducting M4 screws have to be used.




Figure 7. Fixation Points

To avoid mechanical stress of the gate driver during and after the mounting process any bending or warping force imposed to the gate driver must not lead to a vaulting or twisting of the PCB of 0.75 % per axis according to Figure 8:

- Axis 1 and 3: max. 1.4 mm bending
- Axis 2: max. 1.0 mm bending
- Axis 4: max. 1.1 mm bending




Figure 8. Bending Lines

The maximum mounting force for the terminal C is given with  $M_{M4}$ .

As the 1SP0351V2A0C-5SNA3000K452300 is designed for high voltage applications care has to be taken concerning the surrounding area of the gate driver. The gate driver itself possesses a basic isolation with clearance and creepage

distances of  $CLR_{P-S}$  and  $CPG_{P-S,PCB}$ . To maintain this isolation the following distances according to Figure 9 must be kept:

- d<sub>1</sub>: It defines the distance between the surrounding area and any primary-side potential of the gate driver. If the surrounding area is connected to the primary-side GND potential,  $d_1$  can be set to 0 mm. Otherwise  $d_1$  has to be set according to the nearest potential and relevant standard for isolation coordination of the application.
- d<sub>2</sub>: It defines the distance between the surrounding area and the top of the DC/DC transformer. This distance must not be smaller than 20 mm.
- d<sub>3</sub>: It defines the distance between the bottom side of the gate driver PCB and the mounting plate. In case the mounting plate is made of metal and/or is electrically conducting the isolated stand-offs must have a distance as defined in the isolation coordination of the application. In case the mounting plate is non-conducting any surrounding conducting area has to be kept away from the bottom side of the gate driver with a distance of not smaller than 20 mm, i.e.  $d_3 = d_2$ .
- d<sub>4</sub>: It defines the distance between the top side of the gate driver PCB and the surrounding area. The distance must be chosen according to the isolation coordination of the application plus 4 mm (to respect the height of mounted components on top of the gate driver PCB).
- d<sub>5</sub>: It defines the distance between the surrounding area and any secondary-side potential of the gate driver. The distance must be chosen according to the isolation coordination of the application.
- d<sub>6</sub>: It defines the distance between the collector, emitter and/or gate cables to the surrounding area. The minimum distance is defined according to the nearest potential and relevant standard for isolation coordination of the application. However, the distance must not be smaller than 20 mm.




Figure 9. Clearance Distances to Surrounding Areas.

## Cables

The cable from gate driver connector X301 to the power supply is not part of the 1SP0351V2A0C-5SNA3000K452300 gate driver. It is recommended to route the cable with minimum parasitic coupling from the controller to the gate driver. Parasitic coupling in particular to any potential of the secondary-side of the gate driver (i.e. high voltage side) and the AC and/or DC bus bar has to be avoided. Otherwise, increased common-mode currents may circulate, which may cause interferences with command and/or status feedback signals.

## Application Guidelines

The following guidelines are meant to optimize the overall system performance when using 1SP0351V2A0C-5SNA3000K452300 gate drivers in various applications.

### Power Supply

The gate driver has to be supplied by a fixed voltage of typically 15V at V15.

### Gate Output Power Calculation

The gate driver can provide up to 1.8 W of gate output power. This value must not be exceeded to prevent any electrical and/or thermal overload of the 1SP0351V2A0C-5SNA3000K452300 gate driver.

The gate output power is related to the power semiconductor's gate charge  $Q_G$  as stated in the corresponding datasheet, actual switching frequency  $f_{SW}$ , and gate turn-on  $V_{GE(on)}$  and turn-off  $V_{GE(off)}$  voltage and can be estimated according to equation (1).

$$P_g = Q_G \cdot \frac{(V_{GE(on)} - V_{GE(off)})^2}{V_{GE(on)*} - V_{GE(off)*}} \cdot f_{SW} \quad (1)$$

The voltages  $V_{GE(on)*}$  and  $V_{GE(off)*}$  refer to the referenced gate turn-on and turn-off gate voltages of the respective driven power semiconductor datasheet at which the gate charge  $Q_G$  is given.

### DC-Link Design

The mechanical and electrical design of the DC-link of the target application determines during turn-off or diode reverse recovery events of the driven power semiconductor the over voltages  $\Delta V_{CE}$  according to equation (2). Here,  $L_\sigma$  describes the overall DC-link stray inductance (i.e. sum stray inductance of DC-capacitors, DC-link bus bar and power semiconductor) and relevant  $di_C/dt$  the collector current change.

$$\Delta V = L_\sigma \cdot \frac{di_C}{dt} \quad (2)$$

If the over voltage  $\Delta V_{CE}$  plus the applied DC-link voltage  $V_{DC}$  exceed the breakdown voltage of the driven power semiconductor (refer to the reverse bias safe operating area RBSOA resp. to the reverse recovery safe operating area RRSOA), the device may be damaged. In case of excessive turn-off or reverse recovery over voltages, one or more of the following application parameters have to be decreased:

- DC-link voltage  $V_{DC}$
- Stray inductance  $L_\sigma$
- Collector current  $i_C$  (only for turn-off even)

Therefore, during the installation and testing of the target application the actual over voltages  $\Delta V_{CE}$  at different conditions have to be measured.

Note: 1SP0351V2A0C-5SNA3000K452300 gate driver will actively limit any over voltage during turn-off events under normal and over current conditions to safe levels using the implemented Dynamic Advanced Active Clamping scheme. However, it is not recommended that the clamping feature is active during normal switching conditions. It may lead to an over load of the implemented clamping devices. Furthermore, it might lead to an under voltage lock-out (UVLO) condition on

the secondary-side power supply of the gate driver and an increase of the turn-off switching losses.

### Multilevel Topologies


1SP0351V2A0C-5SNA3000K452300 gate driver are designed for 2-level topologies. Operation within 3-level or multilevel designs is, however, also possible:

- Cascaded multilevel topologies on system level like for instance Modular Multilevel Converter (MMC) operating with 2-level topologies within one cell are supported without any restriction (implying that required isolation requirements are fulfilled).
- For 3-level systems the turn-off sequence has to be obeyed by the system controller to avoid overvoltage events, which might lead to an RBSOA (reverse biased safe operating area) violation of the power semiconductor. However, 1SP0351V2A0C-5SNA3000K452300 gate driver have Power Integrations' Dynamic Advanced Active Clamping (DA<sup>2</sup>C) implemented, which enables the gate driver to protect the power semiconductor against over voltage conditions arising by wrong turn-off sequences. The suitability of DA<sup>2</sup>C has to be checked within the target application.

Note: During short-circuit and/or under voltage events, the gate driver will immediately switch-off the respective power semiconductor. No control on the turn-off sequence is given. Therefore, the suitability of 1SP0351V2A0C-5SNA3000K452300 has to be checked on application level for this kind of topology.

### Conformal Coating

The electronic components of the gate driver are protected by a layer of acrylic conformal coating with a typical thickness of 50µm using *ELPEGUARD SL 1307 FLZ/2* from *Lackwerke Peters* on both sides of the PCB. This coating layer increases the product reliability when exposed to contaminated environments.

 Note: Standing water (e.g. condensate water) on top of the coating layer is not allowed as this water will diffuse over time through the layer. Eventually it will form a thin film of conducting nature between PCB surface and coating layer, which will cause leakage currents. Such currents may lead to a disturbance of the performance of the gate driver.

## Reliability Test Items

Test Item	Test Methods and Conditions
<b>Environmental Tests<sup>13</sup></b>	
Mechanical vibrations (sinusoidal)	IEC 60068-2-6, frequency range 10 - 150 Hz (7.5 mm displacement, 20 m/s <sup>2</sup> , 30 min), 3 axis, 20 sweep cycles
Damp heat	IEC 60068-2-78, 65 °C (95 % RH, 24 h) → 25 °C (1 h, DUT operated), 10 cycles
Damp heat cyclic	IEC 60068-2-30, 25 °C / 60 % RH → within 1 h up to 95 % RH → within 3 h up to 60 °C → stable 93 % RH for 12 h → within 3 h down to 25 °C → end at 24 h, 6 cycles
Dry heat	IEC 60068-2-2, 85 °C (48 h, 2 h recovery, operated after 0.5 h)
Cold	IEC 60068-2-1, -40 °C (48 h, 2 h recovery, operated after 0.5 h)
Salt spray	IEC 60068-2-11, 5 % concentration, 35 °C, 48 h → 25 °C, 1 h recovery → DUT operated
Change of temperature	IEC 60068-2-14, -40 °C and 85 °C, holding time 3 h, 10 cycles (read-out after 5 <sup>th</sup> cycle, DUT operated at -10 °C and 70 °C)
<b>Endurance Tests</b>	
High temperature, high load test	$V_{V15} = 15 \text{ V}$ , $P_G = P_{G,max}$ (capacitive load), 85 °C, test duration 1000 h
Thermal cycling	IEC 60068-2-14, -40 °C → 125 °C (5K/min, 500 cycles, DUT unpowered)

## EMC Test Items

Test Item	Test Methods and Conditions
<b>EMC Tests</b>	
Electrostatic discharge immunity	IEC 61000-4-2, contact discharge 8 kV, air discharge 15 kV, terminal test points C, E, G and GND
Radiated noise immunity	IEC 61000-4-3, frequency range 80 – 3000 MHz, sine wave 80% AM modulated (1 kHz), 30 V/m
	IEC 61000-4-3, frequency points 80 / 160 / 380 / 450 / 900 MHz, sine wave 80% AM modulated (1 kHz), 30 V/m, test duration 15 s per frequency point
Fast transient burst immunity	IEC 61000-4-4, capacitive clamp with 50 Ω termination, ±5 kV, 5 kHz (15 ms) and 100 kHz (0.75 ms), test points V15 and GND / C and E with attached power semiconductor, test duration 200 s
Conducted noise immunity	IEC 61000-4-6, frequency range 0.15 – 80 MHz, sine wave 80% AM modulated (1 kHz), 20 V <sub>RMS</sub> , test points V15 and GND
Magnetic field immunity	IEC 61000-4-8, 100 mA (30 s), 1000 A/m (1 – 3 s), 3 axis
	IEC 61000-4-9, 1000 A/m, 5 cycles, 3 axis
	IEC 61000-4-10, 100 A/m, 100 kHz and 1 MHz, 3 axis, test duration 2s
Ring wave immunity	IEC 61000-4-12, line-to-line 2 kV, line-to-ground 4 kV, test points V15 and GND
Damped oscillatory wave immunity	IEC 61000-4-18, common mode 2 kV, differential mode 1 kV, 100 kHz and 1 MHz, test points V15 and GND
Radiated Noise	EN 55032:2015 (CISPR32:2015)

Notes:

1. All environmental tests are conducted on the same sample in the given order of tests.

Product Dimensions - 1SP0351V2A0C-5SNA3000K452300




Figure 10. Dimensions.

## Transportation and Storage Conditions

For transportation and storage conditions refer to Power Integrations' Application Note AN-1501.

## RoHS Statement

We hereby confirm that the product supplied does not contain any of the restricted substances according Article 4 of the RoHS Directive 2011/65/EU in excess of the maximum concentration values tolerated by weight in any of their homogeneous materials.

Additionally, the product complies with RoHS Directive 2015/863/EU (known as RoHS 3) from 31 March 2015, which amends Annex II of Directive 2011/65/EU.

Revision	Notes	Date
A	Final Datasheet	08/20

**For the latest updates, visit our website: [www.power.com](http://www.power.com)**

Power Integrations reserves the right to make changes to its products at any time to improve reliability or manufacturability. Power Integrations does not assume any liability arising from the use of any device or circuit described herein. POWER INTEGRATIONS MAKES NO WARRANTY HEREIN AND SPECIFICALLY DISCLAIMS ALL WARRANTIES INCLUDING, WITHOUT LIMITATION, THE IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, AND NON-INFRINGEMENT OF THIRD PARTY RIGHTS.

The statements, technical information and recommendations contained herein are believed to be accurate as of the date hereof. All parameters, numbers, values and other technical data included in the technical information were calculated and determined to our best knowledge in accordance with the relevant technical norms (if any). They may base on assumptions or operational conditions that do not necessarily apply in general. We exclude any representation or warranty, express or implied, in relation to the accuracy or completeness of the statements, technical information and recommendations contained herein.

No responsibility is accepted for the accuracy or sufficiency of any of the statements, technical information, recommendations or opinions communicated and any liability for any direct, indirect or consequential loss or damage suffered by any person arising therefrom is expressly disclaimed.

**Patent Information**

The products and applications illustrated herein (including transformer construction and circuits external to the products) may be covered by one or more U.S. and foreign patents, or potentially by pending U.S. and foreign patent applications assigned to Power Integrations. A complete list of Power Integrations patents may be found at [www.power.com](http://www.power.com). Power Integrations grants its customers a license under certain patent rights as set forth at <http://www.power.com/ip.htm>.

 **Safety Notice**

The data contained in this datasheet is intended exclusively for technically trained staff. Handling all high-voltage equipment involves risk to life. Strict compliance with the respective safety regulations is mandatory.

Any handling of electronic devices is subject to general specifications for protecting electrostatic-sensitive devices according to international standard IEC 60747-1, Chapter IX or European standard EN 100015 (i.e. the workplace, tools, etc. must comply with these standards). Otherwise, this product may be damaged.

 **Life Support Policy**

POWER INTEGRATIONS PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF POWER INTEGRATIONS. As used herein:

1. A Life support device or system is one which, (i) is intended for surgical implant into the body, or (ii) supports or sustains life, and (iii) whose failure to perform, when properly used in accordance with instructions for use, can be reasonably expected to result in significant injury or death to the user.
2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

The PI logo, TOPSwitch, TinySwitch, SENZero, SCALE, SCALE-iDriver, SCALE-iFlex, Qspeed, PeakSwitch, LYTSwitch, LinkZero, LinkSwitch, InnoSwitch, HiperTFS, HiperPFS, HiperLCS, DPA-Switch, CAPZero, Clamless, EcoSmart, E-Shield, Filterfuse, FluxLink, StakFET, PI Expert and PI FACTS are trademarks of Power Integrations, Inc. Other trademarks are property of their respective companies.

©2020, Power Integrations, Inc.



---

## Power Integrations Worldwide Sales Support Locations

### World Headquarters

5245 Hellyer Avenue  
San Jose, CA 95138, USA  
Main: +1-408-414-9200  
Customer Service:  
Worldwide: +1-65-635-64480  
Americas: +1-408-414-9621  
e-mail: usasales@power.com

### China (Shanghai)

Rm 2410, Charity Plaza, No.  
88 North Caoxi Road  
Shanghai, PRC 200030  
Phone: +86-21-6354-6323  
e-mail: chinasales@power.com

### China (Shenzhen)

17/F, Hivac Building, No. 2,  
Keji Nan 8th Road, Nanshan  
District, Shenzhen, China,  
518057  
Phone: +86-755-8672-8689  
e-mail: chinasales@power.com

### Germany (AC-DC/LED Sales)

Einsteinring 24  
85609 Dornach/Aschheim  
Germany  
Tel: +49-89-5527-39100  
e-mail: eurosales@power.com

### Germany (Gate Driver Sales)

HellwegForum 1  
59469 Ense Germany  
Tel: +49-2938-64-39990  
e-mail: igbt-driver.sales@  
power.com

### India

#1, 14th Main Road  
Vasanthanagar Bangalore-  
560052 India  
Phone: +91-80-4113-8020  
e-mail: indiasales@power.com

### Italy

Via Milanese 20, 3rd. Fl.  
20099 Sesto San Giovanni  
(MI) Italy Phone: +39-024-  
550-8701  
e-mail: eurosales@power.com

### Japan

Kosei Dai-3 Bldg.  
2-12-11, Shin-Yokohama,  
Kohoku-ku  
Yokohama-shi, Kanagawa 222-  
0033 Japan  
Phone: +81-45-471-1021  
e-mail:  
japansales@power.com

### Korea

RM 602, 6FL  
Korea City Air Terminal B/D,  
159-6 Samsung-Dong,  
Kangnam-Gu, Seoul, 135-728,  
Korea  
Phone: +82-2-2016-6610  
e-mail:  
koreasales@power.com

### Singapore

51 Newton Road  
#19-01/05 Goldhill Plaza  
Singapore, 308900  
Phone: +65-6358-2160  
e-mail: singapore-sales@  
power.com

### Taiwan

5F, No. 318, Nei Hu Rd., Sec.  
1  
Nei Hu Dist.  
Taipei 11493, Taiwan R.O.C.  
Phone: +886-2-2659-4570  
e-mail:  
taiwansales@power.com

### UK

Building 5, Suite 21 The  
Westbrook Centre Milton  
Road Cambridge  
CB4 1YG  
Phone: +44 (0) 7823-557484  
e-mail: eurosales@power.com